

Thin Client

# Compact Dual Core Series




## Compact Dual Core Series is the solution that offers an excellent price-performance ratio

Wide range of models based on Praim ThinOX, Microsoft CE 6.0R2, Windows XP Embedded SP3, Windows Embedded Standard 7 SP1

- Wide range of applications: from access to centralized infrastructures such as **Citrix XenApp, XenDesktop, VMware View, Microsoft RDS**, to be used as internet/cloud workstation, or to access IBM iSeries systems
- **Powerful 1GHz Dual Core Processor** with limited power consumption, less than 11 W
- **High reliability and immediate centralized management**, thanks to Praim ThinMan management console
- Fanless, silent, efficient and safe
- Native dual DVI monitor support
- 5 external USB ports, 1 in protected slot, built-in speaker
- Options with built-in **Wi-Fi** and **RS232** serial port
- Video resolution up to 1920 x 1440 with a ratio of 4:3 or 16:9 wide screen
- Small and compact can be installed on the back of the LCD monitor

### CERTIFIED FOR



### OPERATING SYSTEM



Technical specifications	C9010	C9050	C9200	C9100	C9400	C9700	C1000
Processor / Chipset	VIA Eden X2 1GHz Dual Core / VIA VX900						
Power supply	External 100/240VAC 50/60Hz, 12VDC / 3A max						
Power consumption: active / stand-by	10,9W / 0,7W standard model, 12,9W / 0,7W with built-in wireless option						
Device dim. with stand, weight / Packaging dim., weight	42 (W) x 198 (H) x 140 (D) mm, 0,95Kg / 85 (W) x 303 (H) x 295 (D) mm, 2,0 Kg						
Device marks / Power Supply marks	CE, FCC Class B, Energy Star 5.0 / CE, FCC Class B, GS TUV,UL						
Temperature range / humidity	0° ÷ 35° / 20% ÷ 80%						
Security lock	Kensington						
Display resolution / Colors	DDC 4:3, 16:10 WIDE / up to 1920 x 1440 / 32 bit color						
Operating System	ThinOX	ThinOX	ThinOX	CE 6.0 R2	XPe SP3	WES 7 SP1	PXE Boot
RAM Memory / Flash memory	1GB / 1GB	1GB / 2GB	1GB / 2GB	1GB / 1GB	1GB / 2GB	2GB / 4GB	1GB / 0
Peripherals							
USB ports	6 USB 2.0 ports(2 front + 2 rear + 1 in protected slot + 1 internal (reserved for built-in wireless option))						
LAN Ethernet	10/100/1000 BaseT Ethernet RJ45						
Monitor	1 DVI-I port + 1 DVI-D port ( with DVI to VGA adapter included)						
PS/2 Mouse and keyboard	1 PS/2 port, PS/2 mouse and keyboard adapter included, optical mouse included						
Serial Port	1 serial port COM1 (DB9 RS-232) optional (alternatively to DVI-D port)						
Parallel port	with adapter from USB to parallel (Option)						
Audio In MIC / Audio Out Headphones	1 x 1/8 inch jack / 1 x 1/8 inch jack						
Built-in wireless 802.11b/g or 802.11b/g/n	Factory option						
Built-in speaker	Built-in speaker 1W						
Protocols and resident clients	C9010	C9050	C9200	C9100	C9400	C9700	C1000
TCP/IP, DNS, DHCP, FTP, SNMP MIB II	✓	✓	✓	✓	✓	✓	-
Auth. 802.1X Ethernet EAP/PEAP MSCHAPV2	✓	✓	✓		✓	✓	-
Cisco VPN Client	✓	✓	✓		-	-	-
RDP client	7.0	7.0	7.0	06:00	7.0	7.1	-
VMware View 5.1 client	RDP/PCoIP	RDP/PCoIP	RDP/PCoIP		RDP/PCoIP		-
Citrix ICA / PN Agent / Receiver	ICA 12	ICA 12	ICA 12	ICA 11	Receiver 3.0	Receiver 3.1	-
Virtual Bridges VERDE 6.6		SPICE	SPICE				-
Client Ericom PowerTerm WebConnect					✓	✓	-
Leostream / Provision Networks VAS client					-	-	-
Browser		Firefox 11	Firefox 11	IE 6 CE 6.0	IE 7.0	IE 8.0	-
Praim TN5250E/3270 Video/Printer Emulator			✓	✓			-
Praim VT/ASCII Emulator			✓	✓			-
Local PDF Viewer		Acrobat 7	Acrobat 7		Acrobat 7	-	-
Microsoft .NET Framework					2.0	2,0-3,0-3,5	-
Media Player, Wordpad				✓	✓	✓	-
E-mail client		Thunderbird 2.0	Thunderbird 2.0		Outlook Exp.		-
JVM		SUN 1.6	SUN 1.6		-	-	-
Flash Player	Adobe 11	Adobe 11	Adobe 11		-	-	-
Skype voip local client		✓	✓		-	-	-
NX NoMachine Client		✓	✓		-	-	-
X11 native Client		✓	✓				-
VNC Client		✓	✓	✓	-	-	-
Shell script sessions		✓	✓				-
CUPS printing support	✓	✓	✓				-
LPD/LPR and RAW	✓	✓	✓	✓		✓	-
User disk partition		50MB	50MB		~ 1GB	~ 1.5GB	-
Praim USB re-direction support	□	□	□	□	□	□	-
Supported Operating Systems							
Citrix Metaframe 1.7, 1.8, XP, PS 4, 4,5	✓	✓	✓	✓	✓	✓	-
Citrix XenApp 6.0, Citrix XenDesktop 5.0	✓	✓	✓	✓	✓	✓	-
MS Windows 2000/2003/2008 TS	✓	✓	✓	✓	✓	✓	-
Unix/Linux/AIX, NX NoMachine Server		✓	✓	✓	-	-	-
IBM AS/400, IBM S/390			✓	✓	-	-	-
Administration / User interface							
Remote management via Praim ThinMan	Freeware	Freeware	Freeware	Freeware	Freeware	Freeware	-
SW Upgrade / VNC shadow / WakeOn LAN	✓	✓	✓	✓	✓	✓	-
Screen saver with password	✓	✓	✓	✓	✓	✓	-
User interface with Desktop and local application toolbar		✓	✓	✓	✓	✓	-
User interface Zero Client VDI mode (Without local desktop)	✓	✓	✓				-
Support multiple concurrent connections	1 Single	✓	✓	✓	✓	✓	-
Factory Options							
1 serial port COM1 (DB9 RS-232) - Alternatively to the DVI-D port	✓	✓	✓	✓	✓	✓	✓
Built-in wireless 802.11b/g	✓	✓	✓	✓	✓	✓	
Built-in wireless 802.11b/g/n	✓	✓	✓		✓	✓	
Flash disk expansion					4GB	8GB	
DDR3 RAM memory expansion	2GB - 4GB	2GB - 4GB	2GB - 4GB		2GB - 4GB	4GB	2GB - 4GB
Options							
USB to Parallel cable adapter	P/N 80EC00012	P/N 80EC00012	P/N 80EC00012	P/N 80EC00012	P/N 80EC00012	P/N 80EC00012	
105 keys standard USB PC keyboard (Black)	89T110001	89T110001	89T110001	89T110001	89T110001	89T110001	
105 keys PS/2 PC/5250 keyboard	89T110002	89T110002	89T110002	89T110002	89T110002	89T110002	
Add-on Praim Media streaming codecs (76AC00006)	76AC00006	76AC00006	76AC00006				
LCD VESA mounting bracket	80EC0028	80EC0028	80EC0028	80EC0028	80EC0028	80EC0028	80EC0028
External USB 802.11-b/g WiFi dongle	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031	80AC00031
Dual monitor adapter cable from DVI-I to VGA/DVI	80EC00037	80EC00037	80EC00037	80EC00037	80EC00037	80EC00037	80EC00037
Warranty							
3 years ex-factory							
Note:	✓ Available	◊ Installable from the user based on available free disk space	□ Requires ThinMan (TEE or TPE) + TCe VDA				

All names and trademarks contained in this document, are property of their respective owners. The information in this document is property of Praim SRL.

Ver. 1.04

#### ITALY (HQ)

PRAIM SRL - VIA EZIO MACCANI, 191  
38121 TRENTO (TN)  
ITALY

p: +39 0461 420517 | f: +39 0461 420581

INFO@PRAIM.COM - WWW.PRAIM.COM

#### SPAIN

PRAIM SRL - CALLE CALÉNDULA, 93 - MINIPARC III  
EDIFICIO E - 28109 ALCODENDAS (MADRID)  
SPAIN

p: +34 91 790 24 51

INFO@PRAIM.COM - WWW.PRAIM.ES

#### UNITED KINGDOM

PRAIM LTD - LAKESIDE HOUSE, 1 FURZEGROUND WAY  
STOCKLEY PARK, UXBIDGE, UB11 1BD  
UNITED KINGDOM

p: +44 (0)20-8622 3031 | f: +44 (0)20-8622 3303

INFO@PRAIM.COM - WWW.PRAIM.CO.UK